

MIC-DLN

detektor valjanosti novčanica

Precizan detektor valjanosti i brojač novčanica s TFT prikazom, namijenjen svakodnevnom radu s gotovinom.



Provjera: magnetizam i IR



Ekran: TFT LCD



Napajanje: 100-240 V



Baterija: opcija 11.1 V

Ključne prednosti



Provjera
magnetizam i IR



Ekran
TFT LCD



Napajanje
100-240 V



Baterija
opcija 11.1 V



Dimenzije
155 x 137 x 82 mm



Masa
0.5 kg

Idealno za



Blagajne



Maloprodaja



Kontrola gotovine



Usluge

Prikazi uređaja



Glavni prikaz
vizual uređaja



Detalj proizvoda
prikaz opreme

Bočni prikaz
format uređaja



Osnovno

Model	Detektor valjanosti i brojač novčanica
Ekran	TFT LCD za pregled iznosa i broja novčanica
Sučelje	USB za ažuriranje firmwarea



Provjera novčanica

Metode	Magnetizam, infra crveno svjetlo, kvaliteta, veličina i debljina papira
Valute	Prilagođeno za EUR, prikladno za mnoge valute uz firmware
Prikaz	Broj novčanica i ukupna vrijednost po valuti

Napajanje i kućište

Napajanje	AC 100-240 V 50/60 Hz, DC 12 V / 1 A
Baterija	Opcijska punjiva litijska baterija 11.1 V / 500 mAh
Potrošnja	manja od 10 W
Dimenzije	155 x 137 x 82 mm
Masa	0.5 kg

Okolina

Radna temperatura	0 °C do +40 °C
Skladištenje	-20 °C do +40 °C